

DCP-1610WECompact All-In-One Mono Laser Printer with Wi-Fi



Top Features:

Fast Printing

• Help increase productivity with print speeds up to 20ppm

Input Capacity

• 150 sheet paper input capacity

Built-in Wireless Networking

• Share with your workgroup via its built-in wireless 802.11b/g/n network interface

Replacement Cartridges

• Easy replacement 1,000¹ page toner cartridges

High-Quality Output

• Print professional documents with HQ1200 output (2,400 x 600dpi resolution)

Mobile Printing

• Print from anywhere using the Brother iPrint&Scan app











Mono Laser Multifunction Range Datasheet DCP-1610WE & MFC-1910WE



General

Technology	Electrophotographic Laser Printer
Laser Classification	Class 1 laser product (IEC 60825-1:2007)
Processor	200MHz
Local Interface	Hi-Speed USB 2.0
Wireless Network Interface	IEEE 802.11b/g/n
Memory	32MB
Display	2 Line x 16 characters

Driver Compatibility

	Windows 8® (32 & 64 bit editions)
Windows®	Windows 7® (32 & 64 bit editions)
	Windows Vista® (32 & 64 bit editions)
	Windows® XP Professional (32 & 64 bit editions)
	Windows® XP Home Edition
	Windows® Server 2012 & 2008R2*
	Windows® Server 2008 (32 & 64 bit editions)*
	Windows® Server 2003 (32 & 64 bit editions)* *Windows® Server supports network printing only
Macintosh ⁵	OS X 10.7.5, 10.8.x, 10.9.x
Linux ⁵	CUPS, LPD/LPRng (x86/x64 environment)

Printer

Print Speed (A4)	20ppm (pages per minute)
Resolution	HQ1200 (2,400 x 600dpi), 600 x 600dpi
FPOT (First Print Out Time	Less than 10 seconds from ready mode
Warm-Up Time	Less than 18 seconds from sleep mode
Print Languages	GDI

Colour Scanner

Scan Resolution from Scanner Glass	Up to 600 x 1,200dpi
Interpolated Scan Resolution ⁶	19,200 x 19,200dpi
Colour Depth	24bit internal / external colour scanner
Grey Scale	256 shades of grey are available for scanning
Scan Key ⁶	Enables users to scan a document to email, Image, File & SharePoint
Pull Scanning ⁶	Scan to email, Image, File & SharePoint

Printer Functions

N-up Printing ³	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)
Poster Printing ⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Watermark Printing ⁴	Watermark your documents with predefined text or with your own user-defined messages
ID Printing ⁴	Add identification to your printed documents (date & time, short custom message or PC username)
Manual 2-Sided Print ⁴	Manual 2-sided printing
Booklet Printing ⁴	Print documents in A5 booklet format using manual 2-sided print
Skip Blank Page ⁴	Ignores any blank pages in your documents
Print Profiles ³	Store your favourite driver settings as profiles to easily recall them
Print Text In Black ⁴	Converts all text in your documents to black when printed

Scanner Driver

Windows®	TWAIN & WIA (Windows [®] 8, Windows [®] 7, Windows Vista [®] & Windows [®] XP)
Macintosh ⁵	TWAIN & ICA
Linux ⁵	SANE

Paper Handling

Paper Input ²	Standard Tray – 150 sheets
Paper Output ²	Face Down - 50 sheets

Media Specification

Media Types & Weights	Standard Tray - plain & recycled paper (between 65 - 105g/m²)
Media Sizes	Standard Tray - A4, Letter, Legal, Folio, A5, A5(Long Edge), B5, Executive

¹Approx declared yield value in accordance with ISO/IEC 19752

²Calculated with 80g/m² paper ³Windows® & Mac® only

⁴Windows® only

⁵Optional free download from the Brother Solutions Centre http://solutions.brother.com

⁶Requires Brother software

⁷Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your

Mono Laser Multifunction Range Datasheet DCP-1610WE & MFC-1910WE



Copier

Speed – (A4)	Up to 20cpm (copies per minute)
FCOT (First Copy Out Time)	Less than 16 seconds from ready mode
Resolution	600 x 600dpi
Multi-Copying / Stack / Sort	Makes up to 99 copies of each page / Stacks or Sorts
Enlargement / Reduction Ratio	Reduce or Increase document sizes from 25% to 400% in 1% increments
N in 1 Copying	Allows the user to compress 2 or 4 pages on to a single A4 sheet
2in1 ID Copying	Allows the user to copy both sides of an ID card to a single A4 sheet
Grey Scale	256 shades of grey are available for copying

Network & Security

Port/Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client ICMP, Web Services (Print/Scan) NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print/Scan) Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), SMTP-AUTH	Network & Security	
Wireless Applications Vertical Pairing Network Protocols TCP/IP (IPv4 and IPv6) ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client ICMP, Web Services (Print/Scan) NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 1Pv6 (off by default) 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print/Scan) Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), SMTP-AUTH Automatically have the device send an Email to a nominated Email address when it requires attention Pv4 Restrict Restrict which network users either can or	Wireless Network	
Network Protocols TCP/IP (IPv4 and IPv6) ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client ICMP, Web Services (Print/Scan) NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port P100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print/Scan) Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), SMTP-AUTH Automatically have the device send an Email to a nominated Email address when it requires attention IPv4 Restrict Restrict which network users either can or	Wireless Setup Support	
ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client ICMP, Web Services (Print/Scan) NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print/Scan) Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), SMTP-AUTH Automatically have the device send an Email to a nominated Email address when it requires attention Restrict which network users either can or	Wireless Applications	Vertical Pairing
WINS/NetBIOS name resolution, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client ICMP, Web Services (Print/Scan) NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print/Scan) Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), SMTP-AUTH Automatically have the device send an Email to a nominated Email address when it requires attention Restrict WIRELEACTION CONTROL OF THE SERVER OF T	Network Protocols	TCP/IP (IPv4 and IPv6)
Web Services (Print/Scan) Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), SMTP-AUTH Automatically have the device send an Email to a nominated Email address when it requires attention Pv4 Restrict Restrict which network users either can or		WINS/NetBIOS name resolution, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMP, Web Services (Print/Scan) NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server,
(AES), SMTP-AUTH Automatically have the device send an Email to a nominated Email address when it requires attention Restrict Restrict Restrict		
Email Notifications nominated Email address when it requires attention	Wireless Network Security	WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), SMTP-AUTH
IPv4 Restrict	Email Notifications	•
	IPv4 Restrict	

Network Management Utilities

Embedded Web Server	Web based print management software embedded onto the device
Driver Deployment Wizard ⁴	Easily create print drivers for hassle free deployment over your network
BRAdmin Professional 3 ⁴⁸	§ LAN/WAN management software

Mobile Printing & Scanning

iPrint&Scan (Android)	Print directly from or scan directly to a smart phone or tablet running the Android Operating System
iPrint&Scan (iPad / iPhone / iPod)	Print directly from or scan directly to an iPad / iPhone / iPod Touch
iPrint&Scan (Windows® Phone)	Print directly from or scan directly to a smart phone running the Windows® Phone Operating System
Print&Scan (Windows® 8 & RT)	Print directly from or scan directly to a Windows® 8 or Windows RT Tablet

Supplies

1,			
TI	ages ¹		
D	pages		
Carton Contents Toner Cartridge, Drum, Power Supply Co Driver Software For Windows®, Quick Se Guide, PC Interface Cable NOT Included		ws®, Quick Set-l	•
G	e Cable N		, -

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.

Dimensions & Weight

With Carton	481 x 436 x 406 mm 9Kg
Without Carton	385 x 340 x 255mm 7.2Kg

Duty Cycles

Recommended Monthly	250 – 1,800 pages monthly print volume
Maximum Monthly ⁷	Up to 10,000 pages monthly print volume

Environment

Power Consumption	Printing - 390W, ready - 50W, deep sleep – 0.9W, off - 0.28W	
TEC Value	0.7kWh / Week	
Sound Pressure Level	Printing - 52dbA, Ready - 32dbA	
Sound Power Level	Printing - 6.6BA, Ready – 4.7BA	
Power Saving	This enables the printer to consume less energy when not in use	
Toner Saving	This reduces the toner usage and helps to reduce the total cost of printer ownership	
Energy Star	Version 2.0	



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth. www.brotherearth.com



This model is based on the DCP-1610WE plus the additional specification below

MFC-1910WE

Compact All-In-One Mono Laser Printer with Wi-Fi



Compared to DCP-1610WE:

Automatic Document Feeder

• 10 Sheet Automatic document feeder for multiple page scanning, copying & faxing

Fax Capabilities

• 14.4Kbps modem, PC-Fax Send^{6&3}, PC-Fax Receive^{6&4}

All trademarks and registered trademarks referenced herein are the property of their respective companies. Windows, Windows Vista, and the Windows logo are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries. Mac and the Mac logo are trademarks of Apple Inc., registered in the U.S. and other countries.

Mono Laser Multifunction Range Datasheet DCP-1610WE & MFC-1910WE



Fax

Fax Modem	14.4Kbps
Speed Dials	99 locations
PC Fax Send ^{6&3}	Send faxes directly from your PC
PC Fax Receive ^{6&4}	Receive faxes directly to your PC
Automatic Redial	Automatic redialling if the recipient fax is busy
Telephone Index	An electronic, alphabetical listing of stored speed dials and group numbers
Speaker / Ring volume	3 levels and off
Fax / Tel Switch	Automatic recognition of fax and telephone reception
Super Fine	Enables quality transmission of very small print and line drawings
Contrast	Auto / light / dark
Quick-Scan	Reduce scanning times by scanning a fax into memory before sending. Approximately 4.5 seconds per page A4 standard resolution
Memory Transmission	Up to 400 pages (ITU-TTest Chart, Standard Resolution, MMR)
Out of Paper Reception	Up to 400 pages (ITU-TTest Chart, Standard Resolution, MMR)
Dual Access	Allows the operator to perform 2 different tasks on the machine at the same time
Broadcasting	Send the same fax message to up to 119 separate locations (manual 20 locations)
Auto Reduction	When receiving a single page document more than 297mm long the fax machine will automatically reduce the message to fit onto a single A4 sheet
ECM (Error Correction Mode)	The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)
Remote Set-up ⁴	Allows the user to set-up the MFC from their PC
Grey Scale	256 shades of grey are available for faxing

Colour Scanner

Scan Resolution from ADF Up to 600 x 600dpi

Paper Handling

Paper Input ²	ADF – 10 sheets
--------------------------	-----------------

Media Specification

Media Types & Weights	ADF - plain & recycled paper (between 65 - 90g/m²)
Media Sizes	ADF- A4, Letter, Legal, Folio

Environment

Power Consumption	Printing - 390W, ready - 50W, deep sleep – 1.4W, off - 0.3W
TEC Value	0.8kWh / Week

Dimensions & Weight

With Carton	481 x 436 x 425 mm 10.1Kg
Without Carton	385 x 340 x 283mm 8.2Kg

Supplies

	Toner Cartridge, Drum, Power Supply Cord, Fax
Carton Contents	Line Cord, Driver Software For Windows®, Quick
	Set-Up Guide, PC Interface Cable NOT Included

Network & Security

¹Approx declared yield value in accordance with ISO/IEC 19752

²Calculated with 80g/m² paper ³Windows® & Mac® only

⁴Windows® only

⁵Optional free download from the Brother Solutions Centre http://solutions.brother.com

⁶Requires Brother software

⁷ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your