



# PC-Connectable shipping and barcode label printer

QL-1100c



CONTINUOUS ROLL



PRE-SIZED LABELS



PC CONNECTION

[brother.co.uk/QL1100c](http://brother.co.uk/QL1100c)

# PC-Connectable shipping and barcode label printer

The Brother QL-1100c is a high-speed label printer engineered to print up to 4" wide labels. This business-quality label printer lets you create cost-effective paper adhesive labels for packages, envelopes, postage and more.

**QL-1100c**



## Key Features:

- Print labels up to 103.6mm wide and at up to 110mm/second print speed
- USB connectivity for PC and Mac
- Supports printing of FBA (Fulfilled By Amazon) labels through a special PDF crop print function
- Built-in cutter to create your own length labels using unique continuous rolls
- Windows SDK (Software Development Kit) available to add label printing to your own apps

## Your home office business partner

The unique to Brother feature of automatic crop print function enables online sellers to easily print product and other barcode labels instead of using A4/letter size label sheet templates\*. The barcode labels comply with Fulfilled by Amazon requirements.

The Brother QL-1100c delivers fast print speeds of up to 69 standard address labels per minute with black text at 300dpi. Auto cutter allows for printing one or multiple labels at a time, eliminating wasted label sheets. Free P-touch Editor software is included, allowing you to easily design your own labels.

## Included items

Printer  
DK-11247 - Large shipping  
pre-sized labels (41 labels)  
DK-22205 - 62mm width  
continuous roll (8.1 metres)

USB cable  
AC power cord  
Documentation

## Printing / Media

**Printing technology**  
Direct thermal

**Maximum print width**  
101.6mm

**Media sensor type**  
Reflective

**Print resolution**  
1300 x 300dpi

**Minimum label length**  
25.4mm

**Cutter**  
Yes (full cut / guillotine type)

**Maximum print speed\***  
69 standard address labels per  
minute or 110mm per second\*

**Maximum label length**  
3 metres (Windows / MacOS)  
1 metre (P-touch Editor Lite /  
iPrint&Label)\*\*

**Media types**  
DK rolls (DK pre-sized labels /  
DK continuous tape)

**Label widths**  
12mm - 103.6mm

## Control panel

**Buttons**  
Power / Feed / Cut /  
P-touch Editor Lite

## Connectivity

**USB**  
USB version 2.0 full-speed  
(type B)

## Memory

**Flash (for label templates)**  
7.8MB

**Locations  
(for label templates)**  
99

## Power

**Power**  
220-240V AC internal  
power supply

**Energy Star Certification**  
Yes

**Auto sleep mode**  
Yes

## Weights / Dimensions

**Dimensions**  
170 (w) x 222 (d) x 151 (h) mm

**Weight**  
1.71kg

## Software / Firmware

### Operating system support

Windows:  
7, 8, 8.1, 10, 11,  
Server 2008, 2008 R2, 2012,  
2012 R2, 2016, 2019, 2022  
Mac:  
10.11, 10.12, 10.13, 10.14,  
10.15, 11, 12

### Label editor support

P-touch Editor (Windows/Mac)  
Add-In for Microsoft Word/  
Excel/Outlook  
P-touch Editor Lite (Windows)  
iPrint&Label (Android only  
using USB cable)

### Supported printer commands

ESC/P  
P-touch Template  
Raster

### Label crop and print

(convert A4 sheets of labels to  
individual labels automatically).  
Yes (Windows only)

### Barcode symbologies

(using P-touch Editor for  
Windows)  
CODE39, CODE128, UCC/  
EAN128(GS1-128), ITF(I-2/5),  
CODABAR(NW-7), UPC-A,  
UPC-E, EAN13, EAN8,  
ISBN-2 (EAN13 AddOn2),  
ISBN-5 (EAN13  
AddOn5), Laser Barcode,  
POSTNET, RSS(RSS14  
Standard, RSS14  
Truncated, RSS14 Stacked,  
RSS14 Stacked Omni, RSS  
Limited, RSS Expanded, RSS  
Expanded Stacked),  
AztecCode, PDF417 (Standard,  
Truncate, Micro), QR code  
(Model1, Model2, Micro), Data  
Matrix (ECC Square, ECC  
Rectangular), MaxiCode  
(Model2, Model3, Model4,  
Model5), IMB

### Barcode symbologies

(using P-touch Editor for Mac)  
CODE39, CODE128, UCC/  
EAN128(GS1-128), ITF(I-2/5),  
CODABAR(NW-7), UPC-A,  
UPC-E, EAN13, EAN8,  
ISBN-2(EAN13 AddOn2),  
ISBN-5(EAN13 AddOn5),  
Laser Barcode, POSTNET,  
RSS(RSS14 Standard, RSS14  
Truncated, RSS14 Stacked,  
RSS14 Stacked Omni, RSS  
Limited, RSS Expanded, RSS  
Expanded Stacked), PDF417  
(Standard, Truncate, Micro), QR  
code (Model1, Model2, Micro),  
Data Matrix (ECC Square, ECC  
Rectangular), MaxiCode  
(Model2, Model3, Model4,  
Model5), IMB

### Barcode symbologies

(Built-in printer firmware)  
CODE39, CODE128, UCC/  
EAN128(GS1-128), ITF(I-2/5),  
CODABAR(NW-7), UPC-A,  
UPC-E, EAN13, EAN8,  
ISBN-2(EAN13 AddOn2),  
ISBN-5(EAN13 AddOn5), Laser  
Barcode, POSTNET, RSS  
(RSS14 Standard, RSS14  
Truncated, RSS14 Stacked,  
RSS14 Stacked Omni, RSS  
Limited, RSS Expanded, RSS  
Expanded Stacked), PDF417  
(Standard, Truncate, Micro), QR  
code(Model1, Model2, Micro),  
Data Matrix (ECC Square, ECC  
Rectangular), MaxiCode  
(Model2, Model3, Model4,  
Model5), IMB

### Internal fonts

Bitmap fonts: Helsinki, Brussels,  
Letter Gothic Bold, San Diego,  
Brougham. Bitmap font sizes:  
24 dots, 32 dots, 48 dots.  
Outline fonts: Helsinki, Brussels,  
Letter Gothic. Outline font sizes:  
33 dots - 400 dots (22 sizes)

\* Brother standard test environment. Using DK-11201 standard address labels and USB connection.

\*\* Using USB connection through P-touch Editor



### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

[www.brotherearth.com](http://www.brotherearth.com)

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

**brother**  
at your side